



## **OMD 201 UNI-B**

---

**4/6 DIGIT PROGRAMMABLE  
UNIVERSAL LAGRE DISPLAY**

DC VOLTMETER/AMMETER

PROCESS MONITOR

OHMMETER

THERMOMETER FOR PT 100/500/1 000

THERMOMETER FOR NI 1 000

THERMOMETER FOR THERMOCOUPLES

DISPLAYS FOR LIN. POTENTIOMETERS



## SAFETY INSTRUCTIONS

Please, read the enclosed safety instructions carefully and observe them!  
These instruments should be safeguarded by isolated or common fuses (breakers)!  
For safety information the EN 61 010-1 + A2 standard must be observed.  
This instrument is not explosion-safe!

## TECHNICAL DATA

Measuring instruments of the OMD 201 series conform to the European regulation 89/336/EWG and the Ordinance 168/1997 Coll.

The instruments are up to the following European standards:  
EN 55 022, class B  
EN 61000-4-2, -4, -5, -6, -8, -9, -10, -11

The instruments are applicable for unlimited use in agricultural and industrial areas.

## CONNECTION

Supply of energy from the main line has to be isolated from the measuring leads.



## ORBIT MERRET, spol. s r.o.

Vodnanska 675/30  
198 00 Prague 9  
Czech Republic

Tel: +420 - 281 040 200  
Fax: +420 - 281 040 299  
e-mail: orbit@merret.cz  
www.orbit.merret.cz



1.	Contents	3
2.	Instrument description	4
3.	Instrument connection	6
4.	Instrument setting	8
	Symbols used in the instructions	10
	Setting the DP and the (-) sign	10
	Control keys function	11
	Setting/permitting items into "USER" menu	11
5.	Setting "LIGHT" menu	12
5.0	Description "LIGHT" menu	12
	Setting input - type "DC"	16
	Setting input - type "PM"	16
	Setting input - type "OHM"	18
	Setting input - type "RTD - Pt"	19
	Setting input - type "RTD - Ni"	20
	Setting input - type "T/C"	21
	Setting input - type "RTD - Cu"	22
	Setting measuring range for channels B, C, D	24
	Setting projection for channel B	38
	Setting projection for channel C	40
	Setting projection for channel D	42
	Setting Limits	44
	Setting analog output	46
	Setting display colors	48
	Selection of programming menu „LIGHT"/„PROFI"	50
	Restoration of manufacture setting	50
	Calibration - input range (DU)	51
	Selection of instrument menu language version	52
	Setting new access password	52
	Instrument identification	53
6.	Setting "PROFI" menu	54
6.0	Description of "PROFI" menu	54
6.1	"PROFI" menu - INPUT	
6.1.1	Resetting internal values	58
6.1.2	Setting measuring type, range, mode, rate,	59
6.1.3	Setting the Real Time	66
6.1.4	External input function selection	66
6.1.5	Optional accessory functions of the keys	68
6.2	"PROFI" menu - CHANNEL	
6.2.1	Setting measuring parameters (projection, filters, decimal point, description)	72
6.2.2	Setting mathematic functions	76
6.2.3	Selection of evaluation of min/max. value	81
6.3	"PROFI" menu - OUTPUT	
6.3.1	Setting Limits	83
6.3.2	Setting data output	87
6.3.3	Setting analog output	88
6.3.4	Selection of display projection	90
6.4	"PROFI" menu - SERVICE	
6.4.1	Setting the address of IR remote control	92
6.4.2	Selection of programming menu „LIGHT"/„PROFI"	93
6.4.3	Restoration manufacture setting	93
6.4.4	Calibration - input range (DU)	94
6.4.5	Selection of instrument menu language version	95
6.4.6	Setting new access password	95
6.4.7	Instrument identification	96
7.	Setting items into "USER" menu	98
8.	Method of measuring of the cold junction	100
9.	Data protocol	102
10.	Error statements	104
12.	Table of symbols	105
12.	Technical data	106
13.	Instrument dimensions and instalation	108
14.	Certificate of guarantee	109

## 2.1

## Description

The OMD 201 model series are 4/6 digit large panel programmable displays designed for maximum efficiency and user comfort while maintaining their favourable price.

TYPEe OMD 201 UNI is a multifunction instrument with the option of configuration for 7 various input options, easily configurable in the instrument menu. By further options of input modules it is feasible to measure larger ranges of DC voltage and current or increase the number of inputs up to 4 (applies for PM).

The instrument is based on an 8-bit microcontroller with a multichannel 24-bit sigma-delta converter, which secures high accuracy, stability and easy operation of the instrument.

### The OMD 201 is a multifunction instrument available in following types and ranges

#### TYPEe UNI

<b>DC:</b>	$\pm 60/\pm 150/\pm 300/\pm 1200$ mV
<b>PM:</b>	0...5 mA/0...20 mA/4...20 mA/ $\pm 2$ V/ $\pm 5$ V/ $\pm 10$ V/ $\pm 40$ V
<b>OHM:</b>	0...100 $\Omega$ /0...1 k $\Omega$ /0...10 k $\Omega$ /0...100 k $\Omega$ /Auto
<b>RTD-Pt:</b>	Pt 50/100/Pt 500/Pt 1 000
<b>RTD-Cu:</b>	Cu 50/Cu 100
<b>RTD-Ni:</b>	Ni 1 000/Ni 10 000
<b>T/C:</b>	J/K/T/E/B/S/R/N/L
<b>DU:</b>	Linear potentiometer (min. 500 $\Omega$ )

#### TYPEe UNI, option A

**DC:**  $\pm 0,1$  A/ $\pm 0,25$  A/ $\pm 0,5$  A/ $\pm 2$  A/ $\pm 5$  A/ $\pm 100$  V/ $\pm 250$  V/ $\pm 500$  V

#### TYPEe UNI, option B (expansion by 3 more inputs)

**PM:** 3x 0...5 mA/0...20 mA/4...20 mA/ $\pm 2$  V/ $\pm 5$  V/ $\pm 10$  V/ $\pm 40$  V

### PROGRAMMABLE PROJECTION

Selection:	of type of input and measuring range
Measuring range:	adjustable as fixed or with automatic change
Setting:	manual, optional projection on the display may be set in the menu for both limit values of the input signal, e.g. input 0...20 mA > 0...850,0
Projection:	-9999...9999 (-99999...999999)

### COMPENSATION

of conduct:	in the menu it is possible to perform compensation for 2-wire connection
of conduct in probe:	internal connection (conduct resistance in measuring head)
of CJC (T/C):	manual or automatic, in the menu it is possible to perform selection of the type of thermocouple and compensation of cold junctions, which is adjustable or automatic (temperature at the brackets)

### LINEARIZATION

Linearization:\* by linear interpolation in 50 points (solely via OM Link)

### DIGITAL FILTERS

Exponen.average:	from 2...100 measurements
Rounding:	setting the projection step for display

### MATHEMATIC FUCTIONS

Min/max. value:	registration of min./max. value reached during measurement
Tare:	designed to reset display upon non-zero input signal
Peak value:	the display shows only max. or min. value
Mat. operations:	polynome, exponential, root, suma, divide

\* only for type DC, PM, DU

**EXTERNAL CONTROL**

Lock:	control keys blocking
Hold:	display/instrument blocking
Tare:	tare activation/resetting tare to zero
Resetting MM:	resetting min/max value

**2.2 Operation**

The instrument is set and controlled by IR Remote control. All programmable settings of the instrument are performed in three adjusting modes:

<b>LIGHT</b>	<b>Simple programming menu</b> - contains solely items necessary for instrument setting and is protected by optional number code
<b>PROFI</b>	<b>Complete programming menu</b> - contains complete instrument menu and is protected by optional number code
<b>USER</b>	<b>User programming menu</b> - may contain arbitrary items selected from the programming menu (LIGHT/PROFI), which determine the right (see or change) - acces without password

All programmable parameters are stored in the EEPROM memory (they hold even after the instrument is switched off).



Complete instrument operation and setting may be performed via OM Link communication interface, which is a standard equipment of all instruments.

The operation program is freely accessible ([www.orbit.merret.cz](http://www.orbit.merret.cz)) and the only requirement is the purchase of OML cable to connect the instrument to PC. It is manufactured in version RS 232 and USB and is compatible with all ORBIT MERRET instruments. Another option for connection is with the aid of data output RS 232 or RS 485 (without the need of the OML cable).

The program OM LINK in „Basic“ version will enable you to connect one instrument with the option of visualization and archiving in PC. The OM Link „Standard“ version has no limitation of the number of instruments connected.

**2.3 Options**

**Excitation** is suitable for supplying power to sensors and transmitters. It has a galvanic separation.

**Comparators** are assigned to monitor one, two, three or four limit values with relay output. The user may select limits regime: LIMIT/DOSING/FROM-TO. The limits have adjustable hysteresis within the full range of the display as well as selectable delay of the switch-on in the range of 0...99,9 s. Reaching the preset limits is signalled by LED and simultaneously by the switch-on of the relevant relay.

**Data outputs** are for their rate and accuracy suitable for transmission of the measured data for further projection or directly into the control systems. We offer an isolated RS232 and RS485 with the ASCII or DIN MessBus protocol.

**Analog outputs** will find their place in applications where further evaluating or processing of measured data is required in external devices. We offer universal analog output with the option of selection of the type of output - voltage/current. The value of analog output corresponds with the displayed data and its type and range are selectable in Menu.

The instrument supply leads should not be in proximity of the incoming low-potential signals.

Contactors, motors with larger input power should not be in proximity of the instrument.

The leads into the instrument input (measured quantity) should be in sufficient distance from all power leads and appliances. Provided this cannot be secured it is necessary to use shielded leads with connection to ground (bracket E).

The instruments are tested in compliance with standards for use in industrial area, yet we recommend to abide by the above mentioned principles.

### MEASURING RANGES

Type	Input I	Input U
DC	$\pm 60/\pm 150/\pm 300/\pm 1\ 200$ mV	
PM	0...5/20 mA/4...20 mA	$\pm 2/\pm 5/\pm 10/\pm 40$ V
OHM	0...0,1/1/10/100 k $\Omega$ /Autorange	
RTD-Pt	Pt 100/Pt 500/ Pt 1 000	
RTD-Cu	Cu 50/100	
RTD-Ni	Ni 1 000/10 000	
T/C	J/K/T/E/B/S/R/N/L	
DU	Linear potentiometer (min. 500 $\Omega$ )	

### OPTION "A"


Type	Input I	Input U
DC	$\pm 0,1$ A/ $\pm 0,25$ A/ $\pm 0,5$ A to GND (C) $\pm 2$ A/ $\pm 5$ A to GND (B)	$\pm 100$ V/ $\pm 250$ V/ $\pm 500$ V to GND (C)

### OPTION "B"

Type	Input 2, 3, 4/I	Input 2, 3, 4/U
PM	0...5/20 mA/4...20 mA	$\pm 2/\pm 5/\pm 10/\pm 40$ V



**"INPUT - I" may be connected to a maximum of 250 mA, i.e. tenfold overload of the range. Beware of improper connection/confusing the current and voltage inputs. It may cause damage to measuring resistance in the Current Input (15 R).**



**1 Power supply**

**4 Analog output**

**5 Data output**

**6 Relays**

**2 Input**

**3 Input-Option**

**GND**

**AV-I**

**AV-U**

**GND**

**TxD**

**RxD**

**GND**

**L**

**L+**

**DU**

**T/C**

**RTD, OHM, NI**

**EXT. 3**


**EXT. 2**

**EXT. 1**

**EXT. 0**

**DC PM**

**3 Input-Option**



**Option B**

**INPUT-1/U**

**INPUT-2/U**

**INPUT-3/U**

**INPUT-4/U**

**INPUT-2/I**

**INPUT-2/I**

**Option A**

**INPUT-U**

**GND-U/IO.5**

**GND-I5**

**INPUT-I**

**INPUT-I**

**PWR**

**INPUT-U**

**INPUT-U**

**GND-U**

**GND-I**

**INPUT-I**



PROFI

Setting

*profi*

- ▶ For expert users
- ▶ Complete instrument menu
- ▶ Access is password protected
- ▶ Possibility to arrange items of the „User“ menu
- ▶ Tree menu structure

LIGHT

Setting

*light*

- ▶ For trained users
- ▶ Only items necessary for instrument setting
- ▶ Access is password protected
- ▶ Possibility to arrange items of the „User“ menu
- ▶ Linear menu structure

USER

Setting

*profi light**user*

- ▶ For user operation
- ▶ Menu items are set by the user (Profi/Light) as per request
- ▶ Access is not password protected
- ▶ Optional menu structure either tree (PROFI) or linear (LIGHT)



## 4.1 Setting

The instrument is set and controlled by IR Remote control. All programmable settings of the instrument are performed in three adjusting modes:

- LIGHT**      **Simple programming menu**  
 - contains solely items necessary for instrument setting and is protected by optional number code
- PROFI**      **Complete programming menu**  
 - contains complete instrument menu and is protected by optional number code
- USER**      **User programming menu**  
 - may contain arbitrary items selected from the programming menu (LIGHT/PROFI), which determine the right (see or change)  
 - access without password


All programmable parameters are stored in the EEPROM memory (they hold even after the instrument is switched off).

Complete instrument operation and setting may be performed via OM Link communication interface, which is a standard equipment of all instruments.


The operation program is freely accessible ([www.orbit.merret.cz](http://www.orbit.merret.cz)) and the only requirement is the purchase of OML cable to connect the instrument to PC. It is manufactured in version RS 232 and USB and is compatible with all ORBIT MERRET instruments.

Another option for connection is with the aid of data output RS 232 or RS 485 (without the need of the OML cable).

## Scheme of processing the measured signal



Setting and controlling the instrument is performed by means of the Remote control. With the aid of the Remote control it is possible to browse through the operation menu and to select and set the required values.



### Symbols used in the instructions

**DC PM**

**DU OHM RTD T/C**

Indicates the setting for given type of instrument

**DEF**

values preset from manufacture



symbol indicates a flashing light (symbol)



inverted triangle indicates the item that can be placed in USER menu



broken line indicates a dynamic item, i.e. it is displayed only in particular selection/version



after pressing the key the set value will not be stored



after pressing the key the set value will be stored



**30** continues on page 30

### Setting the decimal point and the minus sign

#### DECIMAL POINT

Its selection in the menu, upon modification of the number to be adjusted it is performed by the control key **◀** with transition beyond the highest decade, when the decimal point starts flashing. Positioning is performed by **▲/▼**.

#### THE MINUS SIGN

Setting the minus sign is performed by the key **⊖** on higher decade. When editing the item subtraction must be made from the current number (e.g.: 013 > **⊖**, on class 100 > -87)

## Control keys functions

Key	Measurement	Menu	Setting numbers/selection
	access into USER menu	exit menu	quit editing
	programmable key function	back to previous level	move to higher decade*
	programmable key function	move to previous item	move down*
	programmable key function	move to next item	move up*
	programmable key function	confirm selection	confirm setting/selection
	access into LIGHT/PROFI menu		
>3 s 	direct access into PROFI menu		
		configuration of an item for "USER" menu	
		determine the sequence of items in "USER - LIGHT" menu	

\* alternatively, the setting may be done from the numeric keys of the remote control by selecting directly the number required

## Setting items into „USER“ menu

- in LIGHT or PROFI menu
- no items permitted in USER menu from manufacture
- on items marked by inverted triangle



Legend is flashing - current setting is displayed



- item will not be displayed in USER menu
- item will be displayed in USER menu with the option of setting
- item will be solely displayed in USER menu

## 5.0

## Setting "LIGHT"

## LIGHT

## Simple programming menu

- contains only items necessary for instrument setting and is protected by optional number code

SETTING LIGHT

*light*

- For capable users
- Only items necessary for instrument setting
- Access is password protected
- Possibility to arrange items of the „User“ menu
- Linear menu structure

## Preset from manufacture

Password	"0"
Menu	LIGHT
USER menu	off
Setting the items	<b>DEF</b>



*Upon delay exceeding 60 s the programming mode is automatically discontinued and the instrument itself restores the measuring mode*

Access password  
 1428 **G** PASSw **0**

Active inputs: InPut5  
 Type of input - Channel A: 4. InP, TYPE 1, PN  
 Measuring range - Channel A: MOD E 1, 4-20mA

**RTD OHM**  
 EOnECt: 2-wIrE, FOnRA: 00000.0  
**V/C**  
 EOnECt: EMt. 1bC, C.d.tEn: 23, FOnRA: 00000.0

Measuring range - Channel B: MOD E 2, 4-20mA  
 Measuring range - Channel C: MOD E 3, 4-20mA  
 Measuring range - Channel D: MOD E 4, 4-20mA

**DC PM OHM DU** - Setting projection - Channel A  
 n.In.A: 0, nAR.A: 100, FOn.A: 0000.0

Setting projection - Channel B  
 n.In.B: 0, nAR.B: 100, FOn.B: 0000.0

Setting projection - Channel C  
 n.In.C: 0, nAR.C: 100, FOn.C: 0000.0

Setting projection - Channel D  
 n.In.D: 0, nAR.D: 100, FOn.D: 0000.0

**LIM.L1**: 20, **LIM.L2**: 40, **LIM.L3**: 60, **LIM.L4**: 80  
**Option - comparator**


**EXP.A0**: 120, **n.In.A0**: 0, **nAR.A0**: 100  
**Option - Analog output**

Basic color: COL 0.A: GrEEEn, First color's limit: LIM. 1.A: 3333, Color after first limit: COL. 1.A: rEd, Second color's limit: LIM. 2.A: 6667

Color after second limit: COL. 2.A: OrAnGE, Menu type: nEnU, LIGHt, Return to manufacture calibration: rE.CAL: YES, Return to manufacture setting: rE.SEt: FirEn

**DU** - Calibration - only for "DU"  
 C.n.In: YES, C.nAR: YES, Language selection: LAnG: EnGL, New password: PAS.L1: 0

Identification: IdEnt: YES, Instrument: 0nD201Un1-b, SW version: 63-001, Input: 4. InP, 1428 **Return to measuring mode**





TYPE 1

Selection of the type of instrument

- primary selection of the type of instrument
- performs default setting **DEF** of values from manufacture, incl. calibration
- **DEF** = "PM"

Menu	Type of instrument
DC	DC voltmeter
PM	Process monitor
OHM	Ohmmeter
RTD-Pt	Thermometer for sensors Pt
RTD-Ni	Thermometer for sensors Ni
TC	Thermometer for thermocouples
DU	Display for lin. potentiometer
RTD-Cu	Thermometer for sensors Cu

TYPE "PM"

Example

PM

⌵

rtd-Cu

- Type „DC“ 16
- Type "PM" 16
- Type "OHM" 17
- Type "RTD-Pt" 18
- Type "RTD-Ni" 19
- Type "T/C" 20
- Type "DU" 24
- Type "RTD-Cu" 22

**MODE 1** Selection of the instrument measuring range

**DEF** =  $\pm 60$  mV

MODE 1	Menu	Measuring range
	60mV	$\pm 60$ mV
	150mV	$\pm 150$ mV
	300mV	$\pm 300$ mV
	1200mV	$\pm 1,2$ V

Range  $\pm 150$  mV Example

60 nV 150 nV 300 nV 1200 nV DC

24

**MODE 1** Selection of the instrument measuring range

**DEF** = 4 - 20 mA

MODE 1	Menu	Measuring range
	0-5mA	0...5 mA
	0-20mA	0...20 mA
	4-20mA	4...20 mA
	0.2 V	$\pm 2$ V
	0.5 V	$\pm 5$ V
	0-10 V	$\pm 10$ V
	0-40 V	$\pm 40$ V
	Er.4.20	4...20 mA, with error statement „underflow“ in case of signal less than 3,36 mA

Range 0...20 mA Example

0-5 nA 0-20 nA 4-20 nA ... 0-10 u 0-40 u Er.4-20 PM

24



**NODE 1** Selection of the instrument measuring range

**DEF** = 100  $\Omega$

MODE 1	Menu	Measuring range
	100 R	0...100 $\Omega$
	1.0 K	0...1 k $\Omega$
	10.0 K	0...10 k $\Omega$
	100.0 K	0...100 k $\Omega$

Range 0...10 k $\Omega$  Example

**CONNECT** Selection of the type of sensor connection

**DEF** = 2-wire connection

CONNECT	Menu	Connection
	2-WIRE	2-wire
	3-WIRE	3-wire
	4-WIRE	4-wire

Type of connection - 3 wire > **CONNECT** = 3-WIRE Example



**MODE 1** Selection of the instrument measuring range

**DEF** = Pt 100 (3 850 ppm/°C)

Menu	Measuring range
EU-100	Pt 100 (3 850 ppm/°C)
EU-500	Pt 500 (3 850 ppm/°C)
EU-1K0	Pt 1000 (3 850 ppm/°C)
US-100	Pt 100 (3 920 ppm/°C)
RU-50	Pt 50 (3 910 ppm/°C)
RU-100	Pt 100 (3 910 ppm/°C)

Range - Pt 1 000 > MODE 1 = EU-1K0 Example

EU-100 EU-500 EU-1K0 CONECT




**CONECT** Selection of the type of sensor connection

**DEF** = 2-wire connection

Menu	Connection
2-WIRE	2-wire
3-WIRE	3-wire
4-WIRE	4-wire

Type of connection - 3-wire > CONECT. = 3-WIRE Example

2-wire 3-wire 4-wire MODE 2



**MODE 1** Selection of the instrument measuring range

**DEF** = Ni 1 000 - 5 000 ppm/°C

Menu	Measuring range
5.0-1K	Ni 1 000 (5 000 ppm/°C)
6.2-1K	Ni 1 000 (6 180 ppm/°C)
5.0-10K	Ni 10 000 (5 000 ppm/°C)
6.2-10K	Ni 10 000 (6 180 ppm/°C)

Range - Ni 1 000/5 000ppm > MODE 1 = 5.0-10K Example

5.0-1K 6.2-1K 5.0-10K CONNECT

**CONNECT** Selection of the type of sensor connection

**DEF** = 2-wire connection


Menu	Connection
2-WIRE	2-wire
3-WIRE	3-wire
4-WIRE	4-wire

Type of connection - 3 wire > CONNECT = 3-WIRE Example

2-wire 3-wire 4-wire MODE 2







**MODE 1** Selection of the instrument measuring range

**DEF** = Cu 50 (4 285 ppm/°C)

Menu	Measuring range
428-50	Cu 50 (4 285 ppm/°C)
428-0.1	Cu 100 (4 285 ppm/°C)
426-50	Cu 50 (4 260 ppm/°C)
426-0.1	Cu 100 (4 260 ppm/°C)

Range - Cu 50/4260 ppm > MODE = 426-50 Example

428-50 ◀ ▶ 428-0.1 ◀ ▶ 426-50 ◀ ▶



**CONNECT** Selection of the type of sensor connection


**DEF** = 2-wire connection

Menu	Connection
2-WIRE	2-wire
3-WIRE	3-wire
4-WIRE	4-wire


Type of connection - 3-wire > CONNECT = 3-WIRE Example

2-wire ◀ ▶ 3-wire ◀ ▶









**MODE 4** Selection of the instrument measuring range -

Channel D

---

**DEF** = 4 - 20 mA

MODE 4	Menu	Measuring range
	0-5mA	0...5 mA
	0-20mA	0...20 mA
	4-20mA	4...20 mA
	0-2 V	±2 V
	0-5 V	±5 V
	0-10 V	±10 V
	0-40 V	±40 V
	Er.4-20	4...20 mA, with error statement „underflow“ in case of signal less than 3,36 mA

Range 0...20 mA Example

4-20 nA    0-20 nA    n n b



**min A** Setting display projection for minimum value of input signal

- range of the setting: -99999...999999

- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

**DEF** = 0

Projection for 0 mV > MIN A = 0

Example

**min A**



**max A** Setting display projection for maximum value of input signal

- range of the setting: -99999...999999


- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

**DEF** = 100

Projection for 150 mV > MAX A = 3500

Example

100 100 100 200 300 400  
500 0500 1500 2500 3500 **FO-n.A**



**FD-P.A** Setting projection of the decimal point **DEF** = 0000.00


- positioning of the DP is set here in the measuring mode


---

**Projection of DP on display > 00000.0** Example

0000.00 ◀ 00000.0 ▶ COL 0 A \*subsequent item on the menu depends on instrument equipment

38





**F0-r.N.R** Setting projection of the decimal point **DEF** = 0000.00


---


- positioning of the DP is set here in the measuring mode

**Projection of DP on display > 00000.0** *Example*

0000.00 ◀ 00000.0 ▶  \*subsequent item on the menu depends on instrument equipment

38





FD-r.A.

**Setting projection of the decimal point**

- positioning of the DP is set here in the measuring mode

**DEF** = 0000.00

---

Projection of DP on display > 00000.0

Example

0000.00

▼

00000.0

▼

COL D R


\*subsequent item on the menu depends on instrument equipment

↑

↓

↓

38








**FD-r.N.A** Setting projection of the decimal point **DEF** = 00000.0

- positioning of the DP is set here in the measuring mode

**Projection of DP on display > 000000** Example

00000.0    000000    COL D R \*subsequent item on the menu depends on instrument equipment







**Setting display projection for minimum value of input signal**

- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

- range of the setting: -99999...999999

**DEF = 0**

**Projection for the beginning > MIN A = 0** Example




**Setting display projection for maximum value of input signal**

- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

- range of the setting: -99999...999999

**DEF = 100**

**Projection for the end > MAX A = 5000** Example





FD-r.n.A

Setting projection of the decimal point

DEF = 00000.0

- positioning of the DP is set here in the measuring mode

---

Projection of DP on display > 000000


Example

00000.0

000000

CGL 0 A

\*subsequent item on the menu depends on instrument equipment





**LIM. 2 A** Setting second value for display color change **DEF** = 66.67

- range of setting: -99999...999999

**Display value for 1st color change > LIM. 2 A = 400** Example

66.67 + 0 00 000

200 300 400 COL. 2 A




**COL. 2 A** Selection of display color > after exceeding LIM. 2 A **DEF** = Red

- selection of display color is governed by setting under item LIM. 2 A


- the color changes if the displayed value is higher than the value set in LIM. 2 A

**Selection of display color if the data is > COL. 2 A > orange** Example

rEd OrAnGE OrAnGE







**FD.r.n.b** Setting projection of the decimal point - Channel B **DEF** = 0000.00

- positioning of the DP is set here in the measuring mode

**Projection of DP on display > 00000.0** *Example*

0000.00    00000.0    COL.D.b



**COL.D.b** Selection of display color > primary setting - Channel B **DEF** = Green

**Selection of display color - primary > Red** *Example*

GrEE n    rEd    LIN.1.b

Setting is identical as for "Channel A"



### MIN C Setting display projection for minimum value of input signal - Channel C

- range of the setting: -99999...999999

- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

**DEF** = 0

Projection for 0 mA > MIN C = 25

Example



### MAX C Setting display projection for maximum value of input signal - Channel C

- range of the setting: -99999...999999


- position of the DP does not affect display projection
- the DP is automatically shifted after the value is confirmed

**DEF** = 100

Projection for 20 mA > MAX C = 2500

Example





**FD-R.C** Setting projection of the decimal point - Channel C **DEF** = 0000.00

- positioning of the DP is set here in the measuring mode

Projection of DP on display > 00000.0 Example

0000.00 00000.0 COL.D.C




**COL.D.C** Selection of display color > primary setting - Channel C **DEF** = Green

Selection of display color - primary > Red Example

GrEEen rEd LIn.I.C

Setting is identical as for "Channel A"






**F0rA.d** Setting projection of the decimal point - Channel D **DEF** = 0000.00

- positioning of the DP is set here in the measuring mode

Projection of DP on display > 00000.0 Example

0000.00 ▾ 00000.0 ▾ COL.D d



**COL.D d** Selection of display color > primary setting - Channel D **DEF** = Green

Selection of display color - primary > Red Example

GrEEe ▾ rEd ▾ LIn.1 d

Setting is identical as for "Channel A"

**LIM.L.1** Setting boundary for limit 1

- range of the setting: -99999...999999  
- default "Hysteresis"=0 "Delay"=0

**DEP** = 20

Setting limit 1 > MEZ L1 = 32 Example

**LIM.L.2** Setting boundary for limit 2

- range of the setting: -99999...999999  
- default "Hysteresis"=0 "Delay"=0

**DEP** = 40

Setting limit 2 > MEZ L2 = 53.1 Example

\*subsequent item on the menu depends on instrument equipment

**!**  
Items for "Limits" and "Analog output" are accessible only if incorporated in the instrument.



**LIN.L3** Setting boundary for limit 3

- contingent modification of hysteresis or delay may be performed in "PROFI" menu
- range of the setting: -99999...999999
- default "Hysteresis"=0 "Delay"=0

**DEF** = 60

Setting limit 3 > MEZ L3 = 85 Example

80	61	62	63	64	65
65	75	85	MENU		



**LIN.L4** Setting boundary for limit 4

- contingent modification of hysteresis or delay may be performed in "PROFI" menu
- range of the setting: -99999...999999
- default "Hysteresis"=0 "Delay"=0

**DEF** = 80

Setting limit 4 > MEZ L4 = 103 Example

80	81	82	83	84	85
03	03	03	MENU		

\*subsequent item on the menu depends on instrument equipment

**TYP.A.O.** → [0-20 mA] [E. 4-20] [4-20 mA] [0-5 mA] [0-2 V] [0-5 V] [0-10 V]

**Min.A.O.** → [0]

**Setting the type of analog output**

Menu	Range	Description
0-20mA	0...20 mA	
E. 4-20mA	4...20 mA	with indication of error statement (<3,6 mA)
4-20mA	4...20 mA	
0.5mA	0...5 mA	
0.2 V	0...2 V	
0.5 V	0...5 V	
0-10 V	0...10 V	

**DEF** = 4...20 mA

Type of analog output - 0...10 V > TYP. A.O. = 0-10 V Example

[4-20 mA] [0-5 mA] [0-2 V] [0-5 V] [0-10 V] [Min.A.O.]

**Assigning the display value to the beginning of the AO range**

**Min.A.O.** → [0] **DEF** = 0

- range of the setting: -99999...999999


Display value for the beginning of the AO range > MIN A.O. = 0 Example

[0] [Min.A.O.]

**!**

Items for "Limits" and "Analog output" are accessible only if incorporated in the instrument.





MAX A.O. Assigning the display value to the end of the AO range **DEF** = 100


- range of the setting: -99999...999999

**Display value for the end of the AO range > MAX A.O. = 120** Example

100 100 120 120

NEU

Displayed only with options > **Analog output**



## MENU Setting the menu type LIGHT/PROFI

**LIGHT** > menu LIGHT, a simple menu, which contains only the most essential items necessary for instrument setting  
> linear tree structure

**PROFI** > menu PROF I, a complete menu for complete instrument setting  
> tree menu structure

**DEF** = LIGHT

### Menu LIGHT > MENU = LIGHT

Example

LIGHT  rE.CAL



## rE.CAL. Restoration of manufacture calibration

- in the event of error calibration it is feasible to restore manufacture calibration.

Prior to execution of any modifications you will be asked to confirm your selection. (YES)

### Restoration of manufacture setting > YES

Example

rE.CAL.  YES  rE.SET



## rE.SET. Restoration of manufacture instrument setting

- in the event of error setting the manufacture setting may be restored  
- restoration is performed for the currently selected type of the instrument input (select "FIREM.")

- provided you stored your user setting in the "PROFI" menu, it may also be restored (select "USER")  
- loading manufacture calibration and primary setting of items on the menu (DEF)


### Obnova výrobního nastavení > FIREM.

Example

nAStAv.  FIREM.  LRnG

\* subsequent item on the menu depends on instrument type, for "DU" > "K. MIN"

Type „DC“		52
Type "PM"		52
Type "DU"		52
Type "RTD-Pt"		52
Type "RTD-Ni"		52
Type "T/C"		52
Type "OHM"		51
Type "RTD-Co"		52




**r. MIN** Calibration of input range - the potentiometer traveller in initial position Only for type "DU"

- prior confirming the flashing "YES" sign the potentiometer traveller has to be in given idle position

**Calibration of the beginning of the range > C. MIN** Example

YES




**r. MAX** Calibration of input range - the potentiometer traveller in end position Only for type "DU"


- prior confirming the flashing "YES" sign the potentiometer traveller has to be in given idle position

**Calibration of the end of the range > C. MAX** Example

YES








IdEnt.

### Instrument SW version

- the display shows the type of instrument indication, SW number, SW version and current input setting (Mode)
- if SW version contains a letter in first position, then it is a customer SW
- after the identification is completed the menu is automatically exited and the instrument restores the measuring mode

IDENT.	Packet	Description
1.	Instrument	
2.	SW version	
3.	Number of active inputs	



1428

Return to measuring mode


## 6.0

## Setting "PROFI"

## PROFI

## Complete programming menu

- contains complete instrument menu and is protected by optional number code
- designed for expert users
- preset from manufacture is menu **LIGHT**

 SETTING  
 PROFI
 


- For expert users
- Complete instrument menu
- Access is password protected
- Possibility to arrange items of the „User“ menu
- Tree menu structure

## Switching over to "PROFI" menu

&gt;38




- temporary switch-over to **PROFI** menu, which is suitable to edit a few items
- after quitting **PROFI** menu the instrument automatically switches to **LIGHT** menu
- access is password protected (if it was not set under item N. PASS. =0)




- access into **LIGHT** menu and transition to item „MENU“ with subsequent selection of „PROFI“ and confirmation
- after re-entering the menu the **PROFI** type is active
- access is password protected (if it was not set under item N. PASS. =0)








### ome of PROFi MENU



nAR.Fn ◀

**!**  
 Upon delay exceeding 60 s the programming mode is automatically discontinued and the instrument itself restores the measuring mode


## 6.1 Setting "PROFI" - INPUT



The primary instrument parameters are set in this menu

CLEAR	Resetting internal values
CONFIG.	Selection of measuring range and parameters
RTC	Setting date and time for option with RTC
EXT. In.	Setting external inputs functions
KEYS	Assigning further functions to keys on the instrument

### 6.1.1 Resetting internal values



CL. TAR.	Resetting Tare
TARE A	Tare resetting - Channel A
TARE B	Tare resetting - Channel B
TARE C	Tare resetting - Channel C
TARE D	Tare resetting - Channel D
ALL	Tare resetting - Channel A, B, C and D
CL. MIN.	Resetting min/max value

- resetting memory for the storage of minimum and maximum value achieved during measurement

#### 6.1.2a Selection of measuring rate

InPUtS	CLEAR	rEAd.rS	40.0
CHAnnE	COnt.IG.	InPUtS	20.0
OUtPUt	rEt	In.nOd.	10.0
SERvIC	EMt.In.	SuItCH	5.0
	KEYS	tIM.Su.	2.0
		InP.1	1.0
		nOdE 2	0.5
		nOdE 3	0.2
		nOdE 4	0.1

#### rEAd.rS Selection of measuring rate

- measuring rate very significantly affects the number of active inputs "INPUTS" and evaluation mode "IN.MOD." (the factual measuring rates are listed in chapter Technical data)

40.0	40,0 measurements/s
20.0	20,0 measurements/s
10.0	10,0 measurements/s
5.0	5,0 measurements/s
2.0	2,0 measurements/s
1.0	1,0 measurement/s
0.5	0,5 measurements/s
0.2	0,2 measurements/s
0.1	0,1 measurements/s


#### 6.1.2b Selection of the number of active inputs

InPUtS	CLEAR	rEAd.rS	1. InP.
CHAnnE	COnt.IG.	InPUtS	2. InP.
OUtPUt	rEt	In.nOd.	3. InP.
SERvIC	EMt.In.	SuItCH	4. InP.
	KEYS	tIM.Su.	
		InP.1	
		nOdE 2	
		nOdE 3	
		nOdE 4	

#### InPUtS Selection of the number of active inputs

- measuring rate depends on the number of active inputs (the factual measuring rates are listed in chapter Technical data)

1. InP.	Active input 1
2. InP.	Active inputs 1 and 2
3. InP.	Active inputs 1, 2 and 3
4. InP.	Active inputs 1, 2, 3 and 4


**6.1.2c Selection of measuring mode for multichannel instrument**

**In.NOd** Selection of measuring mode in multichannel instrument

**CYCL** Cyclic measuring on all channels

- instrument evaluates measured data simultaneously on all channels
- selection of cycle very significantly affects measuring rate and depends also on the number of active inputs (factual measuring rates are listed in the chapter Technical data)

**SUltCH** Measuring on selected channel

- instrument evaluates measured data only on selected channel

**6.1.2d Selection of inputs switching**

**SUltCH** Selection of inputs switching


**MANURL** Manual inputs switching

- inputs switching is controlled by selected key on the front panel or selected external input

**AUTON** Automatic inputs switching

- inputs switching is automatic in a time period set in "TIM. SW."

#### 6.1.2e Setting the period for inputs switching




#### t IN. SW. Setting the period for inputs switching

- setting the time period for projection of channels in automatic mode of inputs switching ("AUTOM.")
- range of setting 0,5...99,9 s

**DEF** TIM. SW. = 2 s

#### 6.1.2f Selection of „instrument“ type for channel A



#### tYPE 1 Selection of „instrument“ type for channel A

- selection of particular type of "instrument" is bound to relevant dynamic items

dC	DC voltmeter
Pn	Process monitor
OHM	Ohmmeter
rtd-Pt	Thermometer for Pt xxx
rtd-ni	Thermometer for Ni xxxx
tC	Thermometer pro thermocouples
dU	Display for linear potentiometers
rtd-Lu	Thermometer for Cu xxx

**6.1.2g Selection of measuring range for channel A**

↑

⊖ →

⊖

⊖

DC ←

inPuts	CLARr	rERAdrS	tYPE 1	60nV
CHARnE	CONF 1G	inPuts	nDE 1	150nV
OUtPUL	rEtC	in.nDE	CONF EtE	300nV
SERuIL	EMt.in	SuItCH	CJ.tER	1200nV
	tEYS	tM.Su	Ad.rES	
				<b>PM</b>
		InP. 1	LEARd	0-5nA
				0-20nA
				4-20nA <b>DEF</b>
				0-2u
				0-5u
				0-10u
				0-40u
				Er4-20
				<b>RTD-Pt</b>
				EU-100 <b>DEF</b>
				EU-500
				EU-1k0
				US-100
				rU-50
				rU-100
				<b>RTD-Cu</b>
				428-50 <b>DEF</b>
				428-0.1
				426-50
				426-0.1
				<b>RTD-Ni</b>
				5.0-1t <b>DEF</b>
				6.2-1t
				5.0-10t
				6.2-10t
				<b>OHM</b>
				100r <b>DEF</b>
				1t
				10t
				100t
				<b>DU</b>
				LInPDE <b>DEF</b>
				<b>T/C</b>
				tPc b
				tPc E
				tPc J
				tPc K
				tPc N
				tPc R
				tPc S
				tPc T
				tPc L

↑

⊖

**nDE Selection of instrument measuring range**

Menu	Measuring range
60 mV	±60 mV
150 mV	±150 mV
300 mV	±300 mV
1200mV	±1,2 V
Menu	Measuring range
0-5mA	0..5 mA
0-20mA	0..20 mA
4-20mA	4..20 mA
0-2 V	±2 V
0-5 V	±5 V
0-10 V	±10 V
0-40 V	±40 V
Er4-20	4..20 mA, with error statement „underflow“ in case of signal less than 3.36 mA
Menu	Measuring range
100 R	0...100 Ω
1 k	0...1 kΩ
10 k	0...10 kΩ
100 k	0...100 kΩ
Menu	Measuring range
EU-100	Pt 100 [3 850 ppm/°C]
EU-500	Pt 500 [3 850 ppm/°C]
EU-1k0	Pt 1000 [3 850 ppm/°C]
US-100	Pt 100 [3 920 ppm/°C]
RU-50	Pt 50 [3 910 ppm/°C]
RU-100	Pt 100 [3 910 ppm/°C]
Menu	Measuring range
5.0-1k	Ni 1 000 [5 000 ppm/°C]
6.2-1k	Ni 1 000 [6 180 ppm/°C]
5.0-10k	Ni 10 000 [5 000 ppm/°C]
6.2-10k	Ni 10 000 [6 180 ppm/°C]
Menu	Measuring range
428-50	Cu 50 [4 280 ppm/°C]
428-0.1	Cu 1 00 [4 280 ppm/°C]
426-50	Cu 50 [4 260 ppm/°C]
426-0.1	Cu 100 [4 260 ppm/°C]
Menu	Type of thermocouple
T/C B	B
T/C E	E
T/C J	J
T/C K	K
T/C N	N
T/C R	R
T/C S	S
T/C T	T
T/C L	L

#### 6.1.2h Selection of type of sensor connection for channel A

**RTD** **OHM** **T/C**

Navigation icons: Up, Down, Left, Right, Home, Back, Enter.

INPUTS	CLEAR	REARdS	TYPE 1	2-wIrE	DEF
CHAnnE	CONF IG	INPUTS	NOdE 1	3-wIrE	
OUTPUt	rEtC	In. NOd	CONECT	4-wIrE	
SERuIC	EHt. In.	SuItCH	Ad. rES.		
	KEYS	t.M. Su.	LEARd.		
		InP. 1			
		NOdE 2			
		NOdE 3			
		NOdE 4			

Navigation icons: Up, Down, Left, Right, Home, Back, Enter.

INPUTS	CLEAR	REARdS	TYPE 1	Ink.1tC	DEF
CHAnnE	CONF IG	INPUTS	NOdE 1	Ink.2tC	
OUTPUt	rEtC	In. NOd	CONECT	EHt.1tC	
SERuIC	EHt. In.	SuItCH	C.J. tEM.	EHt.2tC	
	KEYS	t.M. Su.			
		InP. 1			
		NOdE 2			
		NOdE 3			
		NOdE 4			

**CONECT.** Selection of type of sensor connection

**RTD** **OHM**

2-wIrE 2-wire connection

3-wIrE 3-wire connection

4-wIrE 4-wire connection

**T/C**

**Ink.1tC** Measurement without reference thermocouple  
- measuring cold junction at instrument brackets

**Ink.2tC** Measurement with reference thermocouple  
- measuring cold junction at instrument brackets with anti-series connected reference thermocouple

**EHt.1tC** Measurement without reference thermocouple  
- the entire measuring set is working under invaried and constant temperature

**EHt.2tC** Measurement with reference thermocouple  
- when using compensation box




Method and procedure of setting the cold junctions is described in separate chapter on page 100



For thermocouple type "B" the items CONECT. and C.J. TEM. are not available

## 6.1.2i | Setting temperature of cold junction


T/C


**Ad. tEn.** Setting temperature of cold junction

- range 0...99 °C with compensation box
- **DEF** = 23 °C

## 6.1.2j | Offset of the beginning of the measuring range

RTD OHM


**Ad. rES.** Offset of the beginning of the measuring range

- in cases when it is necessary to offset the beginning of the range by certain value, e.g. while using sensor in measuring head
- entered directly in Ohm (0...9999)
- **DEF** = 0



#### 6.1.2k Compensation of 2-wire conduct

**RTD OHM**

Navigation icons: Up, Down, Left, Right, Home, Back, Enter.

INPUTS	CLEAR	REARdS	TYPE 1	YES
CHAnnE	CONF IG	INPUTS	NOdE 1	
OUtPUt	rEtC	In. NOd	COndEct	
SERvIC	EMt. In.	SuItCH	Ad. rES.	
	KEYS	tM. Su.	LEARd.	
		InP. 1		
		NOdE 2		
		NOdE 3		
		NOdE 4		

#### LEARd. Compensation of 2-wire conduct

- for measurement accuracy it is necessary to perform compensation of conduct always in case of 2-wire connection
- prior confirmation of the displayed prompt „YES“ it is necessary to substitute the sensor at the end of the conduct by a short-circuit
- **DEF** = 0

#### 6.1.2l Selection of measuring range for channel B

Navigation icons: Up, Down, Left, Right, Home, Back, Enter.


INPUTS	CLEAR	REARdS	0-5nA	
CHAnnE	CONF IG	INPUTS	0-20nA	
OUtPUt	rEtC	In. NOd	4-20nA	<b>DEF</b>
SERvIC	EMt. In.	SuItCH	0-2u	
	KEYS	tM. Su.	0-5u	
		InP. 1	0-10u	
		NOdE 2	0-40u	
		NOdE 3	Er-4-20	
		NOdE 4		

#### NOdE 2 Selection of instrument measuring range for channel B

Menu	Measuring range
0-5mA	0...5 mA
0-20mA	0...20 mA
4-20mA	4...20 mA
0.2 V	±2 V
0.5 V	±5 V
0-10 V	±10 V
0-40 V	±40 V
Er.4-20	4...20 mA, with error statement „underflow“ in case of signal less than 3.36 mA

\*  
Setting procedure is identical for MOD. 3 and MOD. 4

### 6.1.3 Setting the real time clock



#### r-tC Setting the real time clock (RTC)


**tIME** Time setting

- format 23.59.59

**dAtE** Date setting

- format DD.MM.RR

### 6.1.4a External input function selection



#### EHt. In. External input function selection

**OFF** Input is off

**HOLD** Activation of HOLD

**LOCt. F.** Locking keys on the instrument

**b.PASS** Activation of locking access into programming menu LIGHT/PROFI

**tAR-E** Tare activation

- TARE A, B, C, D, All, Active

**CL.nN** Resetting min/max value

**CL-** Tare resetting

- TARE A, B, C, D, All, Active

**SuCH. 1** Successive switching of channel projection

**SuCH. 2** BCD switching of channel projection - EXT. 1,2

- for operation see the table

- following this choice the setting for "EXT. 2" is automatically restricted

**SuCH. 3** BCD switching of channel projection - EXT. 1,2, 3

- for operation see the table

- following this choice the setting for EXT.2" and "EXT. 3" is automatically restricted



SRuE

Table with operation of external inputs

Channel	EXT. 1	EXT. 2	EXT. 3
FIL. A	0	0	
FIL. B	0	1	
FIL. C	1	0	
FIL. D	1	1	
MF	0	0	1
Min	0	1	1
Max	1	0	1
Max	1	1	1


[ SRuE ] Activation of measured data record in instrument memory (not in standard equipment)

- **DEF** EXT. 1 > HOLD
- **DEF** EXT. 2 > LOCK
- **DEF** EXT. 3 > SWCH. 1

\*

Setting procedure is identical for EXT. 2 and EXT. 3

#### 6.1.4b Selection of function "HOLD"



#### n.HOLD Selection of function "HOLD"


**d ISPL.** "HOLD" locks only the value displayed

**d IS. ARQ.** "HOLD" locks the value displayed and on AO

**d. ARQ. HL.** "HOLD" locks the value displayed, on AO and limit evaluation

**ALL** "HOLD" locks the entire instrument

## 6.1.5a Optional accessory functions of the keys



### Fn LE: Assigning further functions to instrument keys

- „FN. LE.“ > executive functions
- „TMP. LE.“ > temporary projection of selected values
- „MNU. LE.“ > direct access into menu on selected item

- no** Key has no further function
- CL nN** Resetting min/max value
- CL r. t.-** Tare resetting
- TARE A, B, C, D, All, Active
- nEnU** Direct access into menu on selected item
- after confirmation of this selection the "MENU" item is displayed on superior menu level, where required selection is performed
- TEMP. u.** Temporary projection of selected values
- after confirmation of this selection the item "TEMPOR." is displayed on superior menu level, where required selection is performed
- tAr-E -** Tare function activation
- TARE A, B, C, D, All, Active
- SuCH. I** Successive switching of channel projection



#### Presett values of the keybuttons **DEF**:

LEFT	Channel B, after filtration
UP	Channel C, after filtration
DOWN	Channel D, after filtration
ENTER	Channel switching "SWCH. 1"



Setting is identical for LEFT, DOWN, UP and ENTER



The channel in use is the one permanently displayed

#### 6.1.5b Optional accessory functions of the keys - Temporary projection




#### tAP. LE Temporary projection of selected item

- "Temporary" projection of selected value is displayed for the time of keystroke
- "Temporary" projection may be switched to permanent by pressing **Ⓢ** + "Selected key", this holds until the stroke of any key

- nD** Temporary projection is off
- CHAn. -** Temporary projection of "Channel A, B, C or D" value
- F IL. -** Temporary projection of "Channel A, B, C or D" value after processing digital filters
- nARt. Fn.** Temporary projection of "Mathematic functions" value
- n In** Temporary projection of "Min. value"
- nARH** Temporary projection of "Max. value"
- L In 1** Temporary projection of "Limit 1" value
- L In 2** Temporary projection of "Limit 2" value
- L In 3** Temporary projection of "Limit 3" value
- L In 4** Temporary projection of "Limit 4" value
- t InE** Temporary projection of "TIME" value
- dARtE** Temporary projection of "DATE" value
- tAR-E -** Temporary projection of "TARE" value
- TARE A, B, C, D, All, Active
- P.t. -** Temporary projection of "P. TARE" value
- TARE A, B, C, D, Active
- COL d. J.** Temporary projection of "CJC" value

Setting is identical for LEFT, DOWN, UP and ENTER

## 6.1.5c Optional accessory functions of the keys - Direct access to item




## non LE Assigning access to selected menu item

- L In. 1 Direct access to item "LIM 1"
- L In. 2 Direct access to item "LIM 2"
- L In. 3 Direct access to item "LIM 3"
- L In. 4 Direct access to item "LIM 4"

**!**  
Setting is identical for LEFT, DOWN, UP and ENTER



## 6.2 Setting "PROFI" - CHANNELS




The primary instrument parameters are set in this menu

- CHAn.A** Setting parameters of measuring "Channel A"
- CHAn.b** Setting parameters of measuring "Channel B"
- CHAn.C** Setting parameters of measuring "Channel C"
- CHAn.d** Setting parameters of measuring "Channel D"
- nAR.Fn** Setting parameters of mathematic functions
- nIn.nARH** Selection of access and evaluation of Min/max value

### 6.2.1a Display projection

**DC PM DU OHM**



**SEt.A** Setting display projection

**nIn.A** Setting display projection for minimum value of input signal


- range of the setting: -99999...999999
- **DEF** = 0.00

**nAR.A** Setting display projection for maximum value of input signal

- range of the setting: -99999...999999
- **DEF** = 100.00

### 6.2.1b Setting fixed tare

**DC PM DU OHM**




**P.tAR.A** Setting "Fixed tare" value

- setting is designed for the event when it is necessary to firmly shift the beginning of the range by known size
- when setting (P.TAR. A > 0) display shows "T" symbol
- range of the setting: 0...999999
- **DEF** = 0.00



#### 6.2.1c Digital filters



Setting is identical for "Channel B, C and D"

#### CON.F.A. Selection of digital filters

- at times it is useful for better user projection of data on display to modify it mathematically and properly, wherefore the following filters may be used:

**nD** Filters are off

**RUER** Measured data average

- arithmetic average from given number („CON.F.A“) of measured values
- range 2...100

**FLORE** Selection of floating filter

- floating arithmetic average from given number („CON.F.A“) of measured data and updates with each measured value
- range 2...30

**EHPOn** Selection of exponential filter

- integration filter of first prvnho grade with time constant („CON.F.A“) measurement
- range 2...100

**rDUnd** Measured value rounding

- is entered by any number, which determines the projection step (e.g: "CON.F.A"=2,5 > display 0, 2.5, 5,...)

#### CON.F.A. Setting constants

- this menu item is always displayed after selection of particular type of filter

**DEF** = 2

**6.2.1d Projection format - positioning of decimal point**

inPUTS	CHARn A	SEt A	000000
CHARn E	CHARn b	FILEtEr	00000.0
OUTPUT	CHARn C	FD-n. A	0000.00
SEruiC	CHARn d	dESC. A	000.000
	NALEFn	SuItE. A	00.00000
	nIn.NAH	COL. A	0.000000
		FLORE. P	



Setting is identical for "Channel B, C and D"

**FD-n. A Selection of decimal point**

- the instrument allows for classic projection of a number with positioning of the DP as well as projection with floating DP, allowing to display a number in its most exact form „FLOAT.P.“

000000. Setting DT - XXXXX.

00000.0 Setting DT - XXXX.x

**DEF** > **RTD** **T/C**

0000.00 Setting DT - XXXX.xx

**DEF** > **DC** **PM** **DU** **OHM**

000.000 Setting DT - XXX.xxx

00.0000 Setting DT - XX.xxxx

0.000000 Setting DT - X.xxxxx

FLORE. P. Floating DP

**6.2.1e Projection of description - the measuring units**

inPUTS	CHARn A	SEt A	00	0 0 0 0
CHARn E	CHARn b	FILEtEr		0 0 0 0
OUTPUT	CHARn C	FD-n. A		0
SEruiC	CHARn d	dESC. A		
	NALEFn	SuItE. A		
	nIn.NAH	COL. A		



Setting is identical for "Channel B, C and D"

**dESC. A Setting projection of descrpt. for "Channel A"**

- projection of measured data may be extended (at the expense of the number of displayed places) by two characters for description

- description is set by shifted ASCII code, when two first places show the set description and two last characters their code in period 0...95

- description is cancelled by code 00


**RTD** **T/C** **DEF** = °C

**DC** **PM** **DU** **OHM** **DEF** = none



Table of signs on page 105

#### 6.2.1f Selection of channel projection upon switching




! Setting is identical for "Channel B, C and D"

#### SuIt. A Selection of channel projection upon switching

- setting in this item enables the user to select individual measuring channels which will be displayed upon switching the channel functions „SWIT. A“

- no Projection restricted
- CHANnE "Channel A" will be displayed
- FILtEr "Channel A" after modification by digital filter
- CHAN.1 F. Will be displayed "Channel A" and subsequently also "Channel A" after modification by digital filter A

#### 6.2.1g Selection of display color



! Setting is identical for "Channel B, C and D"


#### COL. - Selection of display color

- color selection is controlled through setting under items "LIM. 1 A" and "LIM. 2 A"

- rEd Red color
- GrEEEn Green color
- OrAnGE Orange color

- "COL. 0 x" **DEF** = Green
- "COL. 1 x" **DEF** = Orange
- "COL. 2 x" **DEF** = Red

## 6.2.1h Selection of display color change



↑

Ⓡ →

↶ 1

↑

↓

↑

↓

inPUTS	CHAn A	SEt A	COL. 0 A	33.33
CHAnE	CHAn b	FILtEr	LIM. 1 A	
OUtPUt	CHAn C	FDr.A	COL. 1 A	
SERvIC.	CHAn d	FDr.A	LIM. 2 A	
	NAE FN	SuIt A	COL. 2 A	
	nIn.ARH	COL. A		


Ⓛ Ⓜ Ⓝ Ⓟ Ⓠ Ⓡ Ⓢ Ⓣ Ⓤ Ⓥ Ⓦ Ⓧ Ⓨ Ⓩ

**LIM. - A** Selection of display color change

- under items "LIM.1 A" and "LIM.2 A" is set the limit when display color shall change

- "LIM. 1 A" **DEF** = 33.33
- "LIM. 2 A" **DEF** = 66.67

## 6.2.5a Matematické funkce - volba vstupu



↑

Ⓡ →

↶ 1

↑

↓

↑

↓

inPUTS	CHAn A	inp. A	DEF
CHAnE	CHAn b	NAEH.F	FIL. A
OUtPUt	CHAn C	CO. A	FIL. b
SERvIC.	CHAn d	CO. b	FIL. C
	NAE FN	CO. C	FIL. d
	nIn.ARH	CO. d	ALL. F.
		CO. E	
		CO. F	
		FDr.A.A	
		dESL. A	
		SuIt A	
		COL. A	

**inp. A** Selection of input for calculation of mathematic function

- selection of value from which the mathematic function will be calculated

**OFF** Mathematic functions are off

**FIL. A** From "Channel A" after modification by digital filter


**FIL. b** From "Channel B" after modification by digital filter

**FIL. C** From "Channel C" after modification by digital filter

**FIL. d** From "Channel D" after modification by digital filter

**ALL. F.** From "Channels A, B, C, D" after modification by digital filters

#### 6.2.2b Mathematic functions



#### **nALt.F.** Selection of mathematic functions

On selecting „FIL. -“ in item „INP. M.“

**nULt In.** Polynomial

$$Ax^5 + Bx^4 + Cx^3 + Dx^2 + Ex + F$$

**EHPO.n.** Exponential

$$Ax \cdot e^{\left(\frac{Bx+C}{Dx+E}\right)} + F$$

**rOEt** Root

$$Ax \sqrt{\frac{Bx+C}{Dx+E}} + F$$

On selecting „ALL. F.“ in item „INP. M.“

**SUNn** Sum of the values from channels (inputs)  
 $(A \times KA + B \times KB + C \times KC + D \times KD) \times E + F$

**dIuIdE** Quotient of values from channels (inputs)  
 $(A \times KA + C \times KC) / (B \times KB + D \times KD) \times E + F$

**CO.n. -** Setting constants for calculation of mat. functions

- this menu is displayed only after selection of given mathematic function

6.2.2c **Mathematic functions - decimal point**

inPUTS	CHARn.A	InP. n	000000
CHARn.E	CHARn.b	ARtH. F	00000.0
OUtPUt	CHARn.C	CO.n. A	0000.00
SERvIC.	CHARn.d	CO.n. b	000.000
	ARt.Fn	CO.n. C	00.0000
	nIn.nARH	CO.n. d	0.00000
		CO.n. E	FLOAt.P
		CO.n. F	
		FDr.n. n	
		dESC. n	
		SUIt. n	
		COt. n	

**FDr.n. n** Selection of decimal point

- the instrument allows for classic projection of a number with positioning of the DP as well as projection with floating DP, allowing to display a number in its most exact form „FLOA.P.“

000000. Setting DP - XXXXX.

00000.0 Setting DP - XXXX.x

0000.00 Setting DP - XXXX.xx

000.000 Setting DP - XXX.xxx

00.0000 Setting DP - XX.xxxx

0.000000 Setting DP - X.xxxxx

FLOAt.P Floating DP

**DEF**

6.2.2d **Mathematic functions - measuring units**

inPUTS	CHARn.A	InP. n	00	①②③④
CHARn.E	CHARn.b	ARtH. F		⑤⑥⑦⑧
OUtPUt	CHARn.C	CO.n. A		⑨⑩
SERvIC.	CHARn.d	CO.n. b		
	ARt.Fn	CO.n. C		
	nIn.nARH	CO.n. d		
		CO.n. E		
		CO.n. F		
		FDr.n. n		
		dESC. n		
		SUIt. n		
		COt. n		


**dESC. n** Setting projection of description for "MAT.FN"

- projection of measured data may be extended (at the expense of the number of displayed places) by two characters for description
- description is set by shifted ASCII code, when two first places show the set description and two last characters their code in period 0...95
- description is cancelled by code 00

**DEF** = no description

**!**  
Table of signs on page 105

#### 6.2.2e Mathematic functions - selection of channel projection upon switching




#### SuIt.n Selection of channel projection upon switching

- setting in this item enables the user to select individual measuring channels which will be displayed upon switching the channel functions „SWIT. A“

- n0 Projection restricted
- YES Projection permitted

#### 6.2.2f Selection of display color




#### COL.n Selection of display color

- color selection is controlled through setting under items "LIM. 1 M" and "LIM. 2 M"

- rEd Red color
- GrEE.n Green color
- OrAnGE Orange color

- "COL 0 M" **DEF** = Green
- "COL 1 M" **DEF** = Orange
- "COL 2 M" **DEF** = Red

## 6.2.2g Selection of display color change



LIM. - n

## Selection of display color change


- under items "LIM.1 M" and "LIM.2 M" is set the limit when display color shall change

- "LIM. 1 M" **DEF** = 33.33

- "LIM. 2 M" **DEF** = 66.67




### 6.2.3 Selection of evaluation of min/max value



<b>InP. n.n.</b>	<b>Selection of evaluation of min/max value</b>
-	selection of value from which the min/max value will be calculated
<b>n.0</b>	Evaluation of min/max value is off
<b>CHAn.a</b>	From "Channel A"
<b>FIL.a</b>	From "Channel A" after digital filters processing
<b>CHAn.b</b>	From "Channel B"
<b>FIL.b</b>	From "Channel B" after digital filters processing
<b>CHAn.c</b>	From "Channel C"
<b>FIL.c</b>	From "Channel C" after digital filters processing
<b>CHAn.d</b>	From "Channel D"
<b>FIL.d</b>	From "Channel D" after digital filters processing
<b>Mat.Fn.</b>	From "Mathematic functions"
<b>ALL.CH.</b>	From "Channel A, B, C and D"
<b>ALL.F.</b>	From "Channel A, B, C and D" after digital filters processing

### 6.3 Setting „PROFI“ - OUTPUTS



In this menu it is possible to set parameters of the instrument output signals

**LIMITS** Setting type and parameters of limits

**dRtR** Setting type and parameters of data

output

**An. OUtE** Setting type and parameters of analog

output

**dISP** Setting display projection and brightness

#### 6.3.1a Selection of input for limits evaluation


INPUTS	PARAM	LIM 1	InP.L.i	ZRt-R2
CHANnE	LIM1tS	LIM 2	CH.L.i	CHAN.a
OUTPUT	dRtR	LIM 3	ADd.L.i	FIL.a
SERvIC	AN.dUt	LIM 4	tYP.L.i	CHAN.b
	dISP		LIM.L.i	FIL.b
			HYS.L.i	CHAN.c
			On.L.i	FIL.c
			OFF.L.i	CHAN.d
			PER.L.i	FIL.d
			tIN.L.i	PARt.Fn
				nIn
				NRH
				ALL.t
				ALL.F

**DEF**

InP.L.i	Selection evaluation of limits
-	selection of value from which the limit will be evaluated
n0	Limit evaluation is off
CHAN.a	From "Channel A"
FIL.a	From "Channel A" after digital filters processing
CHAN.b	From "Channel B"
FIL.b	From "Channel B" after digital filters processing
CHAN.c	From "Channel C"
FIL.c	From "Channel C" after digital filters processing
CHAN.d	From "Channel D"
FIL.d	From "Channel D" after digital filters processing
PARt.Fn	From "Mathematic functions"
nIn	From "Min.value"
NRH	From "Max.value"
ALL.CH	From "Channel A, B, C and D"
ALL.F	From "Channel A, B, C and D" after digital filters processing



Setting is identical for LIM 2, LIM 3 and LIM 4



#### 6.3.1b Selection of more channels for limit evaluation

#### CH.L.1 Selection of channels for limit evaluation

- the item is accessible only if items "ALL.CH" or "ALL.F." are set in OUTPUT/LIMITS/LIM 1/INP.L1, when "ALL.CH." is selected descriptions "CH.A...D" are displayed, when "ALL.F." descriptions "F.A...D"
- setting allows to assign arbitrary number of measuring channels to one limit for their evaluation
- the limit is active if at least one value in arbitrary channel exceeds set limit
- **DEF** = YES

Setting is identical for LIM 1, LIM 2, LIM 3 i LIM 4

#### 6.3.1c Selection of type of limit

#### NO.L.1 Selection the type of limit

- HYS.L.1** Limit is in mode "Limit, hysteresis, delay"
  - for this mode the parameters of "LIM. L." are set, at which the limit will shall react, "HYS. L." the hysteresis range around the limit (LIM  $\pm 1/2$  HYS) and time "TIM. L." determining the delay of relay switch-on
- FR.ON..** Frame limit
  - for this mode the parameters are set for interval "ON. L." the relay switch-on and "OFF. L." the relay switch-off
- dOS InG** Dosing limit (periodic)
  - for this mode the parameters are set for "PER. L." determining the limit value as well as its multiples at which the output is active and "TIM. L." indicating the time during which is the output active

Setting is identical for LIM 1, LIM 2, LIM 3 i LIM 4

### 6.3.1.d Selection of type of output

↑

⊖ ⊕

⊖ ⊕

←

→

DEF

inPUTS	LIM1bS	LIM 1	inP.L.1	CLOSE
CHAnnE	dARtR	LIM 2	CH.L.1	OPEN
OUTPUt	An.OUt	LIM 3	NOd.L.1	
SERvIC	dISP.	LIM 4	tYP.L.1	
			LIM.L.1	
			HYS.L.1	
			On.L.1	
			OFF.L.1	
			PER.L.1	
			tIM.L.1	

↑

⊖ ⊕

#### tYP.L.1 Selection of type of output

- CLOSE Output switches on when condition is met
- OPEN Output switches off when condition is met

Setting is identical for LIM 2, LIM 3 and LIM 4

### 6.3.1.e Setting values for limits evaluation

↑

⊖ ⊕

⊖ ⊕

←

→

DEF

inPUTS	LIM1bS	LIM 1	inP.L.1	20
CHAnnE	dARtR	LIM 2	CH.L.1	
OUTPUt	An.OUt	LIM 3	NOd.L.1	
SERvIC	dISP.	LIM 4	tYP.L.1	
			LIM.L.1	
			HYS.L.1	
			On.L.1	
			OFF.L.1	
			PER.L.1	
			tIM.L.1	

↑

⊖ ⊕

#### LIM.L.1 Setting limit for switch-on

- for type "HYSTER"

#### HYS.L.1 Setting hysteresis

- for type "HYSTER"
- indicates the range around the limit (in both directions, LIM.  $\pm 1/2$  HYS.)

#### On.L.1 Setting the outset of the interval of limit switch-on

- for type "FROM.."

#### OFF.L.1 Setting the end of the interval of limit switch-on

- for type "FROM.."

#### PER.L.1 Setting the period of limit switch-on

- for type "DOSING"

- #### tIM.L.1 Setting the time switch-on of the limit
- for type "HYSTER" and "DOSING"
  - setting in range:  $\pm 0...99,9$  s
  - positive time > relay switches after the limit is exceeded (LIM. L1) and time setting (TIM. L1)
  - negative time > relay switches off after the limit is exceeded (LIM. L1) and set negative time (TIM. L1)

Setting is identical for LIM 2, LIM 3 and LIM 4

#### 6.3.2a Selection of data output baud rate

Inputs	Limits	<b>bAud</b>	600
CHARnE	dRAr	Addr.	1200
OUTPUL	Rn. OUT.	Adr. Pb.	2400
SERuIL	dISP.	PrOt	4800
			9600 <b>DEF</b>
			19200
			38400
			57600
			115200
			230400

<b>bAud</b>	Selection of data output baud rate
600	Rate - 600 Baud
1200	Rate - 1 200 Baud
2400	Rate - 2 400 Baud
4800	Rate - 4 800 Baud
9600	Rate - 9 600 Baud
19200	Rate - 19 200 Baud
38400	Rate - 38 400 Baud
57600	Rate - 57 600 Baud
115200	Rate - 115 200 Baud
230400	Rate - 230 400 Baud

#### 6.3.3b Setting instrument address


Inputs	Limits	<b>bAud</b>	0
CHARnE	dRAr	Addr.	
OUTPUL	Rn. OUT.	Adr. Pb.	
SERuIL	dISP.	PrOt	

<b>Addr.</b>	Setting instrument address
	- setting in range: 0...31
<b>DEF</b>	= 00

<b>Adr. Pb.</b>	Setting instrument address - PROFIBUS
	- setting in range: 0...127
<b>DEF</b>	= 0


### 6.3.2c Selection of data output protocol



#### PrOut Selection of the type of analog output

- ASCII** Data protocol ASCII
- n.BUS** Data protocol DIN MessBus

### 6.3.3a Selection of input for analog output




#### InP.AO Selection evaluation analog output

- selection of value from which the analog output will be evaluated

- nD** AO evaluation is off
- CHAn.A** From "Channel A"
- FIL.A** From "Channel A" after digital filters processing
- CHAn.b** From "Channel B"
- FIL.b** From "Channel B" after digital filters processing
- CHAn.C** From "Channel C"
- FIL.C** From "Channel C" after digital filters processing
- CHAn.d** From "Channel D"
- FIL.d** From "Channel D" after digital filters processing
- nAR.Fn** From "Math.functions"
- nIn** From "Min. value"
- nAH** From "Max. value"
- dISPL.** From "Permanently projected display value"




#### 6.3.3b Selection of the type of analog output



#### tYP. R.O. Selection of the type of analog output

- 0-20 mA Type - 0...20 mA
- 0-5 mA Type - 4...20 mA
- with indication of error statement (< 3,0 mA)
- 4-20 mA Type - 4...20 mA
- 0-5 mA Type - 0...5 mA
- 0-2 V Type - 0...2 V
- 0-5 V Type - 0...5 V
- 0-10 V Type - 0...10 V

#### 6.3.3c Setting the analog output range




#### An. OUt. Setting the analog output range

- analog output is isolated and its value corresponds with displayed data. It is fully programmable, i.e. it allows to assign the AO limit points to two arbitrary points of the entire measuring range


**nIn R.O.** Assigning the display value to the beginning of the AO range  
 - range of the setting: -99999...999999  
 - **DEF** = 0

**nRH R.O.** Assigning the display value to the end of the AO range  
 - range of the setting: -99999...999999  
 - **DEF** = 100

**6.3.4a Selection of input for display projection**


PEr.n.	Selection display projection
	- selection of value which will be shown on the instrument display
CHAn.A	From "Channel A"
FIL.A	From "Channel A" after digital filters processing
CHAn.b	From "Channel B"
FIL.b	From "Channel B" after digital filters processing
CHAn.c	From "Channel C"
FIL.c	From "Channel C" after digital filters processing
CHAn.d	From "Channel D"
FIL.d	From "Channel D" after digital filters processing
Mt.Fn.	From "Math.functions"
Min	From "Min.value"
MAx	From "Max.value"

#### 6.3.4b Selection of display brightness




#### brIGht Selection of display brightness

- by selecting display brightness we may appropriately react to light conditions in place of instrument location

- 0% Display is off
- after keystroke display turns on for 10 s
- 25% Display brightness - 25%
- 50% Display brightness - 50%
- 75% Display brightness - 75%
- 100% Display brightness - 100%


## 6.4 Setting "PROFI" - SERVIS



The instrument service functions are set in this menu

<b>Adr. Ir</b>	Setting the address of IR remote control
<b>MEU</b>	Selection of menu type LIGHT/PROFI
<b>rESTOR.</b>	Restore instrument manufacture setting and calibration
<b>CAL Ib</b>	Input range calibration for „DU“ version
<b>LANG.</b>	Language version of instrument menu
<b>n.PASS.</b>	Setting new access password
<b>IdEnt.</b>	Instrument identification


## 6.4.1 Setting the address of IR remote control


**Adr. Ir** Setting the address of IR remote control

- setting the remote control address is inevitable only in case there are other large displays OMD 201 within the reach of IR remote control
- range of the setting is 0...999

**DEF** = 0

#### 6.4.2 Selection of type of programming menu



**!**  
Change of setting is valid upon next access into menu

#### **MENU** Selection of menu type - LIGHT/PROFI

- enables setting the menu complexity according to user needs and skills


**LIGHT** Active LIGHT menu

- simple programming menu, contains only items necessary for configuration and instrument setting  
- linear menu > items one after another

**PROFI** Active PROF I menu

- complete programming menu for expert users  
- tree menu

#### 6.4.3 Restoration of manufacture setting




#### **rEStOr.** Restoration of manufacture setting

- in the event of error setting or calibration, manufacture setting may be restored.

**rE.CAL** Restoration of manufacture calibration of the instrument

- prior executing the changes you will be asked to confirm your selection „YES“



Jobs performed	Restore	
	Calibration	Setting
cancels USER menu rights	✓	✓
deletes table of items order in USER - LIGHT menu	✓	✓
adds items from manufacture to LIGHT menu	✓	✓
deletes data stored in FLASH	✓	✓
cancels or linearization tables	✓	✓
clears tare	✓	✓
clears conduct resistances	✓	✓
restore manufacture calibration	✓	✗
restore manufacture setting	✗	✓

### rE.SETt. Restoration of instrument manufacture setting

**TYPE** Restoration of instrument manufacture setting

- generating the manufacture setting for currently selected type of instrument (items marked DEF)

**USEr** Restoration of instrument user setting

- generating the instrument user setting, i.e. setting stored under SERVIC./RESTOR./SAVE

**SRuE** Save instrument user setting


- storing the user setting allows the operator to restore it in future if needed



After restoration the instrument switches off for couple seconds

#### 6.4.3 Calibration - Input range


DU



### CARL Ib. Input range calibration

- when "C. MIN" is displayed, move the potentiometer traveller to the required minimum position and confirm by „Enter“, calibration is confirmed by "YES"
- when "C. MAX" is displayed, move the potentiometer traveller to required maximum position and confirm by „Enter“, calibration is confirmed by „YES"

#### 6.4.4 Selection of instrument menu language version




#### LANG Selection of instrument menu language version

CZECH Instrument menu is in Czech

AnGL Instrument menu is in English


#### 6.4.5 Setting new access password



#### n.PASS Setting new password for access to LIGHT and PROFi menu

- this selection enables changing number code that blocks the access into LIGHT and PROFi Menu
- range of the number code: 0...9999
- universal password in the event of loss: LIGHT Menu > „8177” PROFi Menu > „7915”

## 6.4.6 Instrument identification

**IdEnt** Projection of instrument SW version


- display shows type identification of the instrument, SW number, SW version and current input setting (Mode)
- if the SW version reads a letter on first position, it is a customer SW


	Packet	Description
IDENT.	1.	Instrument
	2.	SW version
	3.	Number of active inputs





## 7.0 Setting items into "USER" menu

- **USER** menu is designed for users who need to change only several items of the setting without the option to change the primary instrument setting (e.g. repeated change of limit setting)
- there are no items from manufacture permitted in **USER** menu
- on items indicated by inverse triangle  L i
- setting may be performed in **LIGHT** or **PROFI** menu, with the **USER** menu then overtaking the given menu structure



## Setting

*flashing legend - current setting is displayed*



**n0** item will not be displayed in USER menu

**4E5** item will be displayed in USER menu with editing option

**SH0u** item will be solely displayed in USER menu

### Setting sequence of items in "USER" menu

In compiling USER menu from active LIGHT menu the items (max. 10) may be assigned a sequence, in which they will be projected in the menu



#### Example:

Into USER menu were selected these items:

(keys ①) > TARE A, LIM L. 1, LIM L. 2, LIM L. 3, for which we have preset this sequence


(key ②):

TARE A	5
LIM L. 1	0 (sequence not determined)
LIM L. 2	2
LIM L. 3	1

Upon entering USER menu

(key ③) items will be projected in the following sequence: LIM 3 > LIM 2 > TARE A > LIM 1

Instrument with input for temperature measurement with thermocouple allows to set two types of measurement of cold junction.



#### WITH REFERENCE THERMOCOUPLE

- a reference thermocouple may be located in the same place as the measuring instrument or in place with stable temperature/compensation box
- when measuring with reference thermocouple set  $\text{C0nECC}$  in the instrument menu to  $\text{InE2tC}$  or  $\text{EHt2tC}$
- when using a thermostat (a compensation box or environment with constant temperature) set in the instrument menu  $\text{CJCLtEN}$  its temperature (applies for setting  $\text{C0nECC}$  to  $\text{EHt2tC}$ )
- if the reference thermocouple is located in the same environment as the measuring instrument then set in the instrument menu  $\text{C0nECC}$  to  $\text{InE2tC}$ . Based on this selection the measurement of the ambient temperature is performed by a sensor located in the instrument terminal board.

#### WITHOUT REFERENCE THERMOCOUPLE

- inaccuracy originating from the creation of dissimilar thermocouples on the transition point terminal/conductor of the thermocouple is not compensated for in the instrument
- when measuring without reference thermocouple set  $\text{C0nECC}$  in the instrument menu to  $\text{InEtC}$  or  $\text{EHtEtC}$
- when measuring temperature without reference thermocouple the error in measured data may be as much as  $10^{\circ}\text{C}$  (applies for setting  $\text{C0nECC}$  to  $\text{EHtEtC}$ )



The instruments communicate via serial line RS232 or RS485. For communication they use the ASCII protocol. Communication runs in the following format:

ASCII: 8 bit, no parity, one stop bit  
 DIN MessBus: 7 bit, even parity, one stop bit

The transfer rate is adjustable in the instrument menu. The instrument address is set in the instrument menu in the range of 0 ÷ 31. The manufacture setting always presets the ASCII protocol, rate of 9600 Baud, address 00. The type of line used - RS232 / RS485 - is determined by an output board automatically identified by the instrument.

The commands are described in specifications you can find at [na www.orbit.merret.cz/rs](http://na.www.orbit.merret.cz/rs) or in the OM Link program.

### DETAILED DESCRIPTION OF COMMUNICATION VIA SERIAL LINE

Event	Type	Protocol	Transmitted data																			
Data solicitation (PC)	232	ASCII	#	A	A	<CR>																
		MessBus	No - data is transmitted permanently																			
	485	ASCII	#	A	A	<CR>																
		MessBus	<SADR>	<ENQ>																		
Data transmission (instrument)	232	ASCII	>	D	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<CR>			
		MessBus	<SADR>	D	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<ETX>	<BCC>	
	485	ASCII	>	D	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<CR>		
		MessBus	<SADR>	D	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<ETX>	<BCC>	
Confirmation of data acceptance (PC) - OK	485	MessBus	<DLE>	1																		
Confirmation of data acceptance (PC) - Bad			<NAK>																			
Sending address (PC) prior command			<EADR>	<ENQ>																		
Confirmation of address (instrument)			<SADR>	<ENQ>																		
Command transmission (PC)	232	ASCII	#	A	A	N	P	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<CR>			
		MessBus	<STX>	\$	N	P	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<ETX>	<BCC>		
	485	ASCII	#	A	A	N	P	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<CR>			
		MessBus	<SADR>	\$	N	P	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	(D)	<ETX>	<BCC>		
Command confirmation (instrument)	232	ASCII	OK	!	A	A	<CR>															
			Bad	?	A	A	<CR>															
		MessBus	No - data is transmitted permanently																			
	485	ASCII	OK	!	A	A	<CR>															
			Bad	?	A	A	<CR>															
		MessBus	OK	<DLE>	1																	
			Bad	<NAK>																		
Command confirmation (inst.) - OK	485	MessBus	!	A	A	<CR>																
Command confirmation (instrument) - Bad			?	A	A	<CR>																
Instrument identification			#	A	A	1Y	<CR>															
HW identification			#	A	A	1Z	<CR>															
One-time transmission			#	A	A	7X	<CR>															
Repeated transmission			#	A	A	8X	<CR>															

## LEGEND

#	35	23 <sub>H</sub>	Command beginning
A	A	0...31	Two characters of instrument address (sent in ASCII - tens and units, e.g. "01", "99" universal)
<CR>	13	0D <sub>H</sub>	Carriage return
<SP>	32	20 <sub>H</sub>	Space
N, P			Number and command - command code
D			Data - usually characters "0"... "9", ".", "-", ";", (D) - dp. and (-) may prolong data
R	30 <sub>H</sub> ...3F <sub>H</sub>		Relay and tare status
!	33	21 <sub>H</sub>	Positive confirmation of command (ok)
?	63	3F <sub>H</sub>	Negative confirmation of command (point)
>	62	3E <sub>H</sub>	Beginning of transmitted data
<STX>	2	02 <sub>H</sub>	Beginning of text
<ETX>	3	03 <sub>H</sub>	End of text
<SADR>	address +60 <sub>H</sub>		Prompt to send from address
<EADR>	address +40 <sub>H</sub>		Prompt to accept command at address
<ENQ>	5	05 <sub>H</sub>	Terminate address
<DLE>1	16 49	10 <sub>H</sub> 31 <sub>H</sub>	Confirm correct statement
<NAK>	21	15 <sub>H</sub>	Confirm error statement
<BCC>			Check sum -XOR

## RELAY, TARE

Sign	Relay 1	Relay 2	Tare	Change relay 3/4
P	0	0	0	0
Q	1	0	0	0
R	0	1	0	0
S	1	1	0	0
T	0	0	1	0
U	1	0	1	0
V	0	1	1	0
W	1	1	1	0
p	0	0	0	1
q	1	0	0	1
r	0	1	0	1
s	1	1	0	1
t	0	0	1	1
u	1	0	1	1
v	0	1	1	1
w	1	1	1	1

Relay status is generated by command #AA6X <CR>.

The instrument immediately returns the value in the format >HH <CR>, where HH is value in HEX format and range 00<sub>H</sub>...FF<sub>H</sub>. The lowest bit stands for „Relay 1“, the highest for „Relay 8“

ERROR	CAUSE	ELIMINATION
<i>E. d. U<sub>n</sub></i>	Number is too small (large negative) to be displayed	change DP setting, channel constant setting
<i>E. d. O<sub>n</sub></i>	Number is too large to be displayed	change DP setting, channel constant setting
<i>E. t. U<sub>n</sub></i>	Number is outside the table range	increase table values, change input setting (channel constant setting)
<i>E. t. O<sub>n</sub></i>	Number is outside the table range	increase table values, change input setting (channel constant setting)
<i>E. i. U<sub>n</sub></i>	Input quantity is smaller than permitted input quantity range	change input signal value or input (range) setting
<i>E. i. O<sub>n</sub></i>	Input quantity is larger than permitted input quantity range	change input signal value or input (range) setting
<i>CH. H<sub>n</sub></i>	A part of the instrument does not work properly	send the instrument for repair
<i>CH. EE</i>	Data in EEPROM corrupted	perform restoration of manufacture setting, upon repeated error statement send instrument for repair
<i>CH. SE<sub>n</sub></i>	Change of tied item in menu, Data in EEPROM outside the range	change setting if dependent items, perform restoration of manufacture setting, upon repeated error statement send instrument for repair
<i>CH. CL<sub>n</sub></i>	Memory was empty (presetting carried out)	upon repeated error statement send instrument for repair, possible failure in calibration



The instrument allows to add two descriptive characters to the classic numeric formats (at the expense of the number of displayed places). The setting is performed by means of a shifted ASCII code. Upon modification the first two places display the entered characters and the last two places the code of the relevant symbol from 0 to 95. Numeric value of given character equals the sum of the numbers on both axes of the table.

Description is cancelled by entering characters with code

	0	1	2	3	4	5	6	7		0	1	2	3	4	5	6	7
0		i	"	H	S	'	P	'	0	!	"	#	\$	%	&	'	
8	[	]	H	+	,	-		ˆ	8	(	)	*	+	,	-	.	/
16	0	1	2	3	4	5	6	7	16	0	1	2	3	4	5	6	7
24	8	9	=	.	c	=	ˆ	ˆ	24	8	9	:	;	<	=	>	?
32	J	R	b	[	d	E	F	G	32	@	A	B	C	D	E	F	G
40	H	I	J	K	L	M	N	O	40	H	I	J	K	L	M	N	O
48	P	Q	R	S	T	U	V	W	48	P	Q	R	S	T	U	V	W
56	H	Y	Z	[	\	]	^	_	56	X	Y	Z	[	\	]	^	_
64	'	R	b	c	d	E	F	G	64	`	a	b	c	d	e	f	g
72	h	i	j	k	l	m	n	o	72	h	i	j	k	l	m	n	o
80	P	Q	R	S	T	U	V	W	80	p	q	r	s	t	u	v	w
88	H	Y	Z	+	!	ˆ	ˆ	ˆ	88	x	y	z	{		}	~	

**INPUT - CHANNEL A**

range is adjustable

±60 mV	>100 MOhm
±150 mV	>100 MOhm
±300 mV	>100 MOhm
±1200 mV	>100 MOhm

**DC**

Input U  
Input U  
Input U  
Input U

range is adjustable

0/4...20 mA	< 400 mV
±2 V	1 MOhm
±5 V	1 MOhm
±10 V	1 MOhm
±40 V	1 MOhm

**PM**

Input I  
Input U  
Input U  
Input U  
Input U

range is adjustable

0...100 Ohm
0...1 kOhm
0...10 kOhm
0...100 kOhm

**OHM**

Connection:

2, 3 or 4 wire

Pt xxxx

-200°...850°C

Pt xxxx/3910 ppm

-200°...1 100°C

Ni xxxx

-50°...250°C

Cu/4260 ppm

-50°...200°C

Cu/4280 ppm

-200°...200°C

Type Pt:

EU &gt; 100/500/1 000 Ohm, with 3 850 ppm/°C

US &gt; 100 Ohm, with 3 920 ppm/°C

RU &gt; 50/100 Ohm, with 3 910 ppm/°C

Type Ni:

Ni 1 000/ Ni 10 000 with 5 000/6 180 ppm/°C

Type Cu:

Cu 50/Cu 100 with 4 260/4 280 ppm/°C

Connection:

2, 3 or 4 wire

**RTD**

range is adjustable in configuration menu

Type:

J (Fe-CuNi) -200°...900°C

K (NiCr-Ni) -200°...1 300°C

T (Cu-CuNi) -200°...400°C

E (NiCr-CuNi) -200°...690°C

B (PtRh30-PtRh6) 300°...1 820°C

S (PtRh10-Pt) -50°...1 760°C

R (Pt13Rh-Pt) -50°...1 740°C

N (Omegalloy) -200°...1 300°C

L (Fe-CuNi) -200°...900°C

**T/C****DU**

Voltage of lin. pot.

2,5 VDC/6 mA

min. potentiometer resistance is 500 Ohm

**INPUT - CHANNEL B**

range is adjustable

0/4...20 mA	< 400 mV
±2 V	1 MOhm
±5 V	1 MOhm

**PM**

Input I  
Input U  
Input U

±10 V

1 MOhm

Input U

±40 V

1 MOhm

Input U

**INPUT - CHANNEL C**

range is adjustable

0/4...20 mA	< 400 mV
±2 V	1 MOhm
±5 V	1 MOhm
±10 V	1 MOhm
±40 V	1 MOhm

**PM**

Input I  
Input U  
Input U  
Input U  
Input U

**INPUT - CHANNEL D**

range is adjustable

0/4...20 mA	< 400 mV
±2 V	1 MOhm
±5 V	1 MOhm
±10 V	1 MOhm
±40 V	1 MOhm

**PM**

Input I  
Input U  
Input U  
Input U  
Input U

**PROJECTION**

Display:

999999, intensive red/green/orange  
7-mi segment LED, digit height 57, 100, 125 mm

Projection:

-99999...999999

Decimal point:

adjustable - in menu

Brightness:

adjustable - in menu

**INSTRUMENT ACCURACY**

TC:

100 ppm/°C

Accuracy:

±0,1 % of range + 1 digit

±0,15 % of range + 1 digit

**RTD, T/C****Above accuracies apply for projection 9999**

Resolution:

0,01°/0,1°/1°

**RTD**

Rate:

0,1...40 measurements/s, see table

Overload capacity:

10x (t < 100 ms) not for 250 V and 5 A,  
2x (long-term)

Linearisation:

by linear interpolation in 50 points  
- solely via OM Link

Digital filters:

Averaging, Floating average, Exponential filter, Rounding

Comp. of conduct:

max. 40 Ohm/100 Ohm

**RTD**

Comp. of cold junct.:

adjustable

**T/C**

0°...99°C or automatic

Functions:

Tare - display resetting  
Hold - stop measuring (at contact)  
Lock - control key locking  
MM - min/max value  
Mathematic functions

OM Link:

company communication interface for setting, operation  
and update of instrument SW

Watch-dog:

reset after 400 ms

Calibration:

at 25°C and 40 % of r.h.

\* values apply for resistance load

**COMPARATOR**

Type: digital, adjustable in menu  
 Mode: Hysteresis, From, Dose  
 Limits: -99999...999999  
 Hysteresis: 0...999999  
 Delay: 0...99,9 s  
 Outputs: 4x relays with switch-off contact (Form C)  
 (250 VAC/50 VDC, 5 A)\*  
 Relay: 1/8 HP 277 VAC, 1/10 HP 125 V, Pilot Duty D300

**DATA OUTPUTS**

Protocols: ASCII, DIN MessBus  
 Data format: 8 bit + no parity + 1 stop bit (ASCII)  
 7 bit + even parity + 1 stop bit (MessBus)  
 Rate: 600...230 400 Baud  
 RS 232: isolated, two-way communication  
 RS 485: isolated, two-way communication,  
 addressing (max. 31 instruments)  
 PROFIBUS Data protocol SIEMENS

**ANALOG OUTPUT**

Type: isolated, programmable with resolution of max. 10 000 points, analog output corresponds with displayed data, type and range are adjustable  
 Non-linearity: 0,2 % of range  
 TC: 100 ppm/°C  
 Rate: response to change of value < 40 ms  
 Voltage: 0...2 V/5 V/10 V  
 Current: 0...5/20 mA/4...20 mA  
 - compensation of conduct to 500 Ohm/12 V  
 or 1 000 Ohm/24 V

**EXCITATION**

Adjustable: 5...24 VDC/max. 1,2 W, isolated

**POWER SUPPLY**

Options: 10...30 V AC/DC, max. 27 VA, isolated  
 - fuse inside (T 4 A)  
 80...250 V AC/DC, max. 27 VA, isolated  
 - fuse inside (T 4 A)

**MECHANIC PROPERTIES**

Material: anodized aluminum, black  
 Dimensions: see chapter 13  
 Panel cut-out: see chapter 13




**OPERATING CONDITIONS**

Connection: connector terminal board,  
 conductor cross-section <1,5 mm<sup>2</sup> /<2,5 mm<sup>2</sup>  
 Stabilisation period: within 15 minutes after switch-on  
 Working temp.: 0°...60°C  
 Storage temp.: -10°...85°C  
 Cover: IP64  
 Construction: safety class I  
 Overvoltage category: EN 61010-1, A2  
 Insulation resistance: for pollution degree II, measurement category III  
 instrum.power supply > 670 V (PI), 300 V (DI)  
 Input/output > 300 V (PI), 150 (DI)  
 EMC: EN 61000-3-2+A12; EN 61000-4-2, 3, 4, 5, 8, 11;  
 EN 55022, A1, A2

Table of measuring rate depending on the number of inputs

Channels/Rate	40	20	10	5	2	1	0,5	0,2	0,1
Qty. of channels: 1 (Type: DC, PM, DU)	40,00	20,00	10,00	5,00	2,00	1,00	0,50	0,20	0,10
Qty. of channels: 2	5,00	2,50	1,25	1,00	0,62	0,38	0,22	0,09	0,05
Qty. of channels: 3	3,33	1,66	0,83	0,66	0,42	0,26	0,14	0,06	0,03
Qty. of channels: 4	2,50	1,25	0,62	0,50	0,31	0,19	0,11	0,05	0,02
Qty. of channels: 1 (Type: OHM, RTD, T/C)	5,00	2,50	1,25	1,00	0,62	0,38	0,22	0,09	0,05
Qty. of channels: 2	3,33	1,066	0,83	0,66	0,42	0,26	0,14	0,06	0,03
Qty. of channels: 3	2,50	1,25	0,62	0,50	0,31	0,19	0,11	0,05	0,02
Qty. of channels: 4	2,00	1,00	0,50	0,40	0,25	0,15	0,08	0,04	0,02

PI - Primary insulation, DI - Double insulation

**Side view****Panel cut-out**


Height	X	Y	X1	Y1
<b>57</b>	372	116	364	108
<b>100-4</b>	465	181	457	173
<b>100-6*</b>	677	181	669	173
<b>100-6</b>	647	181	639	173
<b>125-4</b>	539	237	531	228
<b>125-6</b>	754	237	746	228

Tolerance:  $\pm 1$  mm

Panel thickness: 0,5 ... 50 mm

## Wall mounting

As a standard, large displays are designed for panel installation. Upon request we may also supply a holder for wall mounting, see picture.



Product **OMD 201UNI - B**  
 Type .....  
 Manufacturing No. ....  
 Date of sale .....

# GUARANTEE

A guarantee period of 60 months from the date of sale to the user applies to this instrument.  
 Defects occurring during this period due to manufacture error or due to material faults shall be eliminated free of charge.

For quality, function and construction of the instrument the guarantee shall apply provided that the instrument was connected and used in compliance with the instructions for use.

The guarantee shall not apply to defects caused by:

- mechanic damage
- transportation
- intervention of unqualified person incl. the user
- unavoidable event
- other unprofessional interventions

The manufacturer performs guarantee and post.guarantee repairs unless provided for otherwise.

# YEARS

Stamp, signature





# DECLARATION OF CONFORMITY

**Company:** **ORBIT MERRET, spol. s r.o.**  
Klánská 81/141, 142 00 Prague 4, Czech Republic, IDNo: 00551309

**Manufactured:** **ORBIT MERRET, spol. s r.o.**  
Vodňánská 675/30, 198 00 Prague 9, Czech Republic

declares at its full responsibility that the product presented hereunder meets all technical requirements, is safe for use when utilised under the terms and conditions determined by ORBIT MERRET, spol.s r.o. and that our company has taken all measures to ensure conformity of all products of the type listed hereunder, which are being brought out to the market, with technical documentation and requirements of the appurtenant statutory orders.

**Product:** 4/6-digit programmable panel instrument

**Type:** **OMD 201**

**Version:** UNI, PWR, UQC

Conformity is assessed pursuant to the following standards:

El. safety: EN 61010-1  
EMC: EN 50131-1, chapter 14 and chapter 15  
EN 61000-11  
EN 61000-4-11  
EN 61000-4-2  
EN 61000-4-3  
EN 61000-4-6  
EN 61000-4-4  
EN 61000-4-8  
EN 60003-2+A12, Cor. 1, A1, A2  
EN 55022, chapter 5 and chapter 6

and Ordinance on:

El. safety: No. 168/1997 Coll.  
EMC: No. 169/1997 Coll.

The evidence are the protocols of authorized and accredited organizations:

VTÚE Praha, experimental laboratory No. 1158, accredited by ČIA  
VTÚPV Vyškov, experimental laboratory No. 1103, accredited by ČIA

Place and date of issue: Prague, 12. Juni 2001

Miroslav Hackl v.r.  
Company representative

*Mode of asses. of conformity §12, par. 4 b, d Act No. 22/1997 Coll.*